



**Note: This API calls are shared between DOS and Win16 personality.**

DPMI is a shared interface for DOS applications to access Intel 80286+ CPUs services. DOS DMPI host provides core services for protected mode applications. Multitasking OS with DOS support also provides DMPI in most cases. Windows standard and extended mode kernel is a DPMI client app. Standard and extended mode kernel differs minimally and shares common codebase. Standard Windows kernel works under DOSX extender. DOSX is a specialized version of 16-bit DPMI Extender (but it is standard DPMI host). Standard mode is just DPMI client, enhanced mode is DPMI client running under Virtual Machine Manager (really, multitasker which allow to run many DOS sessions). Both modes shares DPMI interface for kernel communication. The OS/2 virtual DOS Protected Mode Interface (VDPMI) device driver provides Version 0.9 DPMI support for virtual DOS machines. Win16 (up to Windows ME) provides Version 0.9 DPMI support. Windows in Standard Mode provides DPMI services only for Windows Applications, not DOS sessions.

DPMI host often merged with DPMI extender. Usually DPMI extender provide DPMI host standard services and DOS translation or True DPMI services.

2021/08/05 10:15 · prokushev · [0 Comments](#)

## Int 31H, AH=0BH, AL=00H

### Version

0.9

### Brief

Set Debug Watchpoint

### Input

AX = 0B00H  
BX:CX = linear address of watchpoint  
DL = size of watchpoint (1, 2, or 4 bytes)  
DH = type of watchpoint

Value	Breakpoint Type
0	execute
1	write
2	read/write

## Return

```
if function successful
Carry flag = clear
BX = watchpoint handle

if function unsuccessful
Carry flag = set
AX = error code
8016H    too many breakpoints
8021H    invalid value (in DL or DH)
8025H    invalid linear address (linear address not mapped or alignment
error)
```

## Notes

Sets a debug watchpoint at the specified linear address.

Under DPMI 1.0, the handle will be in the range 0-14. Under DPMI 0.9, the handle range is not limited.

The watchpoint handle corresponds to the bit number in the Virtual DR6 returned in the exception frame (see Int 31H Function 0212H and page 18 of the DPMI spec).

## See also

## Note

Text based on <http://www.delorie.com/djgpp/doc/dpmi/>

DPMI	
Process manager	<a href="#">INT 2FH 1680H, 1687H</a>
Signals	
Memory manager	
Misc	<a href="#">INT 2FH 1686H, 168AH</a>
Devices	

2021/08/13 14:23 · prokushev · [0 Comments](#)

From:  
<https://cocorico.osfree.org/doku/> - **osFree wiki**

Permanent link:  
<https://cocorico.osfree.org/doku/doku.php?id=en:docs:dpmi:api:int31:0b:00>

Last update: **2021/08/27 06:25**



